



## WF - 8900 Power Centers

Item:	Specification:				
<b>Model Number</b>	<b>WF - 8935</b>	<b>WF - 8945</b>	<b>WF - 8955</b>	<b>WF - 8965</b>	<b>WF - 8975</b>
<b>Power Output</b>	600 W	780 W	950 W	1260 W	1300 W
<b>Input Voltage</b>	105 Vac - 130 Vac / 60 Hz				
<b>Output Current</b>	35 A	45 A	55 A	65 A	75 A
<b>Converter Type</b>	3 Stage Converter/Charger				
<b>Voltage Output</b>	13.2 - 14.4 Vdc				
<b>Absorption Mode</b>	13.6 Vdc (nominal voltage)				
<b>Bulk Mode</b>	14.4 Vdc (quick charging voltage)				
<b>Float Mode</b>	13.2 Vdc (trickle charge voltage)				

### Safety Features/Protections:

<b>Over Current</b>	Yes	Yes	Yes	Yes	Yes
<b>Over Temperature</b>	Yes	Yes	Yes	Yes	Yes
<b>Over Voltage</b>	Yes	Yes	Yes	Yes	Yes
<b>Reverse Polarity</b>	Yes	Yes	Yes	Yes	Yes
<b>Short Circuit</b>	Yes	Yes	Yes	Yes	Yes
<b>Cooling Fan</b>	Yes	Yes	Yes	Yes	Yes

### Shipping:

<b>Outside Dimensions:</b>	13.875" (W) x 11.625" (H) x 9" (D)				
<b>Weight</b>	6.75 lbs.	8.0 lbs.	8.0 lbs.	8.0 lbs.	8.0 lbs.

### Installation: (applies to all models)

**AC Circuits:** 6 (Main and 5 branch circuits)

**DC Circuits:** 11 (9 20A max)  
(2 30A max)

**Case Material** Plastic  
(brown -ANP and black -ANPB)

### Standards: (applies to all models)

**Comply with FCC** Yes



WF-8935/45/55



WF-8965/75



WF-89xxANP/T30  
30A Transfer Switch  
(option)



WF-89xxMBA  
(Converter replacement)

Specifications are subject to change without notice or obligation.

website: <http://www.wfcoelectronics.com>